Hållare för 3,6 V litiumbatteri

Art nr: SP015



SP015 Batterihållare är avsedd att användas som ett tillbehör för batteridrivna omvandlare med radioutgång till Sigfox-nätet (från Wx8xx-serien).

Den gör det möjligt att driva omvandlaren med en eller två 3,6 V litiumbatterier, storlek "C", vilket förlänger drifttiden upp till sex gånger jämfört med standardlivet för ett inbyggt batteri av storlek "AA". Den är utrustad med en anslutningsadapter som monteras istället för omvandlarens interna batteri. SP015 Batterihållare är lämplig för tillämpningar där livslängden för det interna batteriet inte räcker till och där nätanslutning (med valfria tillbehör) inte kan användas.

SP015 Batterihållare levereras separat, utan batterier. Den är designad för primära litiumbatterier 3,6 V, storlek "C". Vi rekommenderar att använda Tadiran SL2770/S batterier (beställningskod A4206). En eller två batterier kan monteras.

Tekniska specifikationer

GENERAL TECHNICAL DATA	
Recommended batteries	Tadiran SL2770/S, lithium, 3.6 V, size"C"
Output voltage	3.6 V DC
Continuous output current	max. 200 mA
Short circuit protection of output	NO (recommended batteries are not dangerous in the event of a short circuit)
Power output	connection adapter for transducers Wx8xx
Working position	vertically, cable glanddown
IP protection	IP65 (after mounting the connection adapter to the Wx8xx sensor)
Operating temperature	-30 to +60 °C
Weight without batteries	200g(including connection adapter)
Dimensions	120 x 93 x 43 mm